


## **ASSEMBLY INSTRUCTIONS**

PARTS & HARDWARE INCLUDED: Do not remove components from cartons prior to assembly. Use the packing list to locate components. Keep hardware kits in labeled packaging until ready to use.




**NOTE**: There will be hardware remaining after assembling in-line workstations.

## **ASSEMBLY TIPS**


- Lay tops upside down before you begin assembly of the Frames & Legs. Pay attention to the orientation of the Tops (rear inserts are closer to the edge).
- Front of Frames bears the Workplace nameplate.
- Hand-tighten all hardware until specified otherwise.
- Two people are required to turn the assembly workstation right-side-up.

## ADJUSTING THE WORKHEIGHT

- Legs are typically set at 34"H and adjust in 1-1/2" increments.
- Remove the hardware from above and below the horizontal crossmember and adjust the leg extender. Replace hardware & tighten securely.



Position Frames flush to rear edge of Worksurfaces. Position Swaybrace on Frame then insert and hold Half Joining Plate (KIT-21C) boss side face down in open Frame end. Fasten Swaybrace to Frame using KIT-21, engaging the half Joining Plate. Repeat on other end and with second Frame/Swaybrace.



- Fasten Leg Sections to Frames using KIT-81. Using the remaining hardware in KIT-21, fasten Swaybraces to Legs. Tighten hardware.
- Fasten framework to the Worksurfaces using KIT-84, note that Z clips are used in center and flat clips on ends.

**NOTE:** Make sure components are properly aligned.

MOBILE IN-LINE ASSEMBLIES: Follow above instructions for basic assembly. Refer to Standard Workstation - Mobile Assembly Instructions to attach Casters and Mobile Supports.